



PACKAGE CONTENTS


PART	DESCRIPTION	QUANTITY	
		P500507	P500508
A	Fixture	1	1
B	Glass Shade	1	1
C	Knurled Nut with Stud	3	3
D	Steel Bracket	3	3
E	Screws	3	3
F	Rubber washer	6	6
G	Knurled Nut	3	3
H	Canopy	1	1





P500507



P500508



HARDWARE CONTENTS (not actual size)

AA  Wire Connector Qty:3	BB  Mounting Plate (installed in canopy) Qty:1	CC  Flat Head Screws (#8-32) (installed in canopy) Qty:2	DD  Chain (72") Qty:1	
--	---	---	--	--

THANK YOU for selecting Progress Lighting

We can assist you with questions regarding product information, assembly or missing parts



800-447-0573

8am-8pm (Eastern), Monday-Friday



customerservice@progresslighting.com



Safety Information

Please read and understand this entire manual before attempting to assemble, operate or install the product.

CAUTION: Read instructions carefully and turn electricity off at main circuit breaker panel before beginning installation.

CAUTION: Risk of fire. Min. 90°C supply conductors. Consult a qualified electrician to ensure correct branch circuit conductor.

WARNING: If any Special Control Devices are used with this fixture, follow instructions carefully to assure full compliance with N.E.C. requirements. If there are any questions, contact a qualified electrical contractor.

CAUTION: All glass is fragile. Use care when handling glass shades and bulbs.

Preparation


1. Before beginning installation, make sure all parts are included using the contents diagrams from page 1. If any part is missing or damaged, do not attempt to assemble, install or operate the product.
2. Estimated assembly time: 30 minutes.
3. Tools required for assembly (not included): Phillips screwdriver, pliers, wire stripper, safety glasses, electrical tape, ladder.

Care and Maintenance

Shut off main power supply before cleaning product or changing light bulbs. To clean, wipe with damp cloth. Do not use abrasive cleaners or cleaners that contain alcohol.


Assembly Instructions

1. Attach the mounting plate (BB) to the outlet box using the mounting screws supplied with the outlet box. Tighten securely.




2. Install the three brackets (D) onto the fixture (A) body using knurled nuts with studs (C).

Attach the fixture (A) assembly to the glass shade (B) by aligning the bracket (D) holes (labeled side up) with the glass shade (B) holes. Insert screws (E) through the rubber washers (F), bracket (D) holes, and glass (B) holes, then add another set of rubber washers (F) and secure them with the knurled nuts (G).



HANGING ASSEMBLY INSTRUCTIONS

3




NOTE: During this step, determine the hanging length of your fixture by removing chain links (DD) and optionally cutting the electrical and ground wire to length.

Do NOT cut electrical or ground wires until this overall length is determined. Leave AT LEAST 6 inches MINIMUM of wire past the canopy chain loop to allow for easy connections in step 4.

(Chain links can be spread open with 2 pairs of pliers. Twist the split link ends in opposite directions and close by squeezing them back together.)

3. Once the hanging length is determined, open both ends of the chain link (DD) and hook it onto the fixture loop (A) and canopy (H) loop. Use pliers to securely close the chain links. Weave the wires through every third chain link (DD). Continue passing the wires through the canopy (H) loop.

4




4. Strip 3/8" of insulation from the electrical wire ends. Using wire connectors (AA), connect the RIBBED fixture wire to the WHITE supply wire from the outlet box; connect the SMOOTH fixture wire to the BLACK supply wire from the outlet box.

Connect the fixture ground wire and supply ground wire using a wire connector or by fastening it to the ground screw on the mounting plate.

Push all of the wire connections carefully into the outlet box.


5



5. Attach the canopy (H) to the mounting plate (BB) using screws (CC) to secure it tightly.

HANGING ASSEMBLY INSTRUCTIONS


6



6. Thread the lamps (not included) into the fixture sockets. Use 75-watt MAX incandescent or SBLED medium base lamps.


CEILING ASSEMBLY INSTRUCTIONS

7a




7a. Remove the chain loop from the canopy (H) by removing the lock washer and hex nut.

7b



7b. Remove the chain loop from the fixture (A).


7c



7c. Attach the canopy (H) onto the nipple of the fixture (A) and install the lock washer and hex nut.

CEILING ASSEMBLY INSTRUCTIONS


8



8. Connect wires as shown in step 4.

Attach the canopy (H) to the mounting plate (BB) using screws (CC) to secure it tightly.

9



9. Thread the lamps (not included) into the fixture sockets. Use 75-watt MAX incandescent or SBLED medium base lamp.

WARRANTY AND EXCLUSIVE REMEDY: Progress products, when properly installed and under normal conditions of use, are warranted to our customers only to be free from defects in material and workmanship at time of shipment. All warranty claims must be asserted within one year from date of purchase of the subject items; thereafter, warranty claims will not be honored. Customers' sole remedy for a warranty claim or otherwise shall be limited to repair or replacement of the subject product if it is shown to have been defective in material or workmanship at time of shipment. Progress's sole and maximum liability for a defective product shall never exceed the cost of the subject product. **EXCEPT FOR SUCH A WARRANTY AND EXCLUSIVE REMEDY AS STATED (AND THE EXPRESS WARRANTY OF TITLE), WE DISCLAIM ALL OTHER WARRANTIES, WHETHER EXPRESS OR IMPLIED, AND SPECIFICALLY DISCLAIM THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. IN NO EVENT SHALL WE BE LIABLE TO CUSTOMER IN WARRANTY, CONTRACT, NEGLIGENCE, STRICT LIABILITY OR OTHERWISE, FOR ANY DAMAGES, WHETHER INCIDENTAL OR CONSEQUENTIAL, WHICH ARE ALLEGED TO BE CAUSED BY ONE OR MORE OF OUR PRODUCTS, BEYOND THE COST TO THE CUSTOMER OF THE SUBJECT PRODUCT OR PRODUCTS.** Therefore, the customer's sole and exclusive remedy against us for breach of the warranty, breach of contract or negligence or strict liability or otherwise shall be limited to repair or replacement of the subject product at our option (excluding installation and removal charges which shall not be our liability) or, if we choose, refund of the purchase price. In no case does our warranty and exclusive remedy extend to anybody other than our customers. Our customers are not authorized to extend warranties or remedies on our behalf to anyone. Such unauthorized extensions of warranties or remedies by the customer shall remain customer's responsibility. Customer is responsible for determining the suitability of our products for customer's use or resale, or for incorporating them into objects or for applications which customer designs, assembles, constructs or manufactures.

Instructions d'Assemblage et Installation


Mise en garde: Lire les instructions avec soin et couper le courant au disjoncteur central avant de commencer l'installation.

MISE EN GARDE: Lire les instructions avec soin et couper le courant au disjoncteur central avant de commencer l'installation.

MISE EN GARDE: Risque d'incendie. Min 90°C conducteurs d'alimentation. Consulter un électricien qualifié pour assurer le bon conducteur de circuit de dérivation.

AVERTISSEMENT - S'il y a d'autres mécanismes régulateurs qui s'emploient avec ce dispositif, suivre soigneusement les instructions pour satisfaire aux exigences NEC. Si vous avez des questions, consulter un électricien qualifié.

MISE EN GARDE - Le verre est toujours fragile; maniez le(s) composant(s) et/ou l' (les) ampoule(s) avec prudence.



Instrucciones de ensamblaje e instalación

Precaución: Lea cuidadosamente las instrucciones y desconecte la electricidad del cortacircuitos principal antes de iniciar la instalación.

PRECAUCIÓN: Lea cuidadosamente las instrucciones y desconecte la electricidad del cortacircuitos principal antes de iniciar la instalación.

PRECAUCIÓN: Riesgo de fuego. Min. 90°C los cables de suministro. Consulte a un electricista calificado para asegurarse de que el conductor del circuito derivado correcto.

ADVERTENCIA - Si usa algún dispositivo especial de control con este aparato de luz, siga las instrucciones cuidadosamente para asegurar la completa conformidad con los requisitos N.E.C. Si existe alguna duda, contacte un electricista calificado.

PRECAUCION - El vidrio es frágil; tenga cuidado al manipular el (los) elemento(s) de vidrio y/o la(s) bombilla(s).

