

MARKOR LED

Ceiling stem mounted • Damp location listed

Specifications:

Description:

The Markor Series is a modular pendant system. The versatile series allow the choice of shades and stem kits. This one-light LED stem mounted pendant is for use with Markor Shades. Shades sold separately. This stem may be used with all Markor shades 9"-22" sizes. Includes two 6", one 12" and two 15" stems with 90 degree swivel.

Construction:

- Brushed Nickel (-09) (plated)
- Steel construction
- LED Module is replaceable (Part # 93053641)
- Flicker-free dimming to 10% brightness with most ELV type dimmers (See Dimming Notes)
- CA Title 24 compliant
- Canopy covers a standard 4" hexagonal recessed outlet box
- 6 Links 9 gauge chain supplied
- Mounting strap for outlet box included
- 10 feet of wire supplied

Performance:

| | |
|---------------------|---|
| Number of Modules | 1 |
| Input Power | 17W |
| Input Voltage | 120V |
| Input Frequency | 60Hz |
| Lumens/LPW | 1,211/71.2 (LM-79) per module |
| CCT | 3000K |
| CRI | 90 |
| Life | 60000 (L70/TM-21) |
| EMI/RFI | FCC Title 47, Part 15, Class B |
| Min. Start Temp | -30 |
| Max. Operating Temp | 30 |
| Warranty | 5 year warranty |
| Labels | cCSAus Damp location listed ENERGY STAR® qualified |

P5198-0930K9

Images:



Dimensions:

Diameter: 5-3/4"
Height: 5-3/8"
Overall ht. w/stem: 62"

Catalog number:

| Base | Finish | Color Temp | CRI |
|-------|---------------------|-------------|------------|
| P5198 | 20 - Brushed Nickel | 30K - 3000K | 9 - 90 CRI |



MARKOR LED

Ceiling stem mounted • Damp location listed



P5198-0930K9

Dimming Notes:

P5198 is designed to be compatible with many Electronic Low Voltage (ELV-Reverse Phase) controls.

The following is a partial list of known compatible dimmer controls:

Electronic Low Voltage ELV Reverse Phase Controls

| | | |
|--------|-------------|--------------------------|
| Lutron | Diva Series | (Part Number DVELV-300P) |
|--------|-------------|--------------------------|

Digital type dimmers are not recommended.

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation.
Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.