

P560071 Wall Lantern

Wall mounted • Wet location listed **PROGRESS LED**



Description:

Outdoor wall lanterns from the Pier 33 collection feature coastal undertones and a design reminiscent of industrial spaces. LED and incandescent options are comprised of a die-cast frame. Clear seeded glass complements a Black finish.

Specifications:

- Black (-031) (painted)
- Aluminum Etched Seeded Glass diffuser
- Black finish
- Coastal undertone.
- Design reminiscent of industrial spaces.
- Clear seeded glass.
- 624 lumens 66 lumens/watt
- 3000K color temperature, 90+ CRI
- Dimmable to 10% with many ELV dimmers
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- ENERGY STAR® qualified
- Meets California Title 24 JA8-2016

Performance:

Number of Modules	1
Input Power	9w
Input Voltage	120 V
Input Frequency	
Lumens/LPW	624/66 (LM-79)
CCT	3000 K
CRI	90 CRI
Life (hours)	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30°C
Warranty	5 year limited warranty
Labels	cCSAus Wet location listed
	ENERGY STAR® qualified
	Meets California Title 24 JA8-2016

P560071-031-30

Images:



Dimensions:

Width: 8-1/8"
 Depth: 9"
 Height: 8"
 H/CTR: 3-1/8"

Glass
 Width: 6-5/8"
 Height: 5-1/2"

P560071 Wall Lantern

Wall mounted • Wet location listed



P560071-031-30

Dimming Notes:

P560071 is designed to be compatible with many Triac/ELV controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P

Lutron Nova T NTELV-300

Lutron Caseta

Lutron Ariadni AY-600P

Leviton Illumatech IPI06-1LZ

Leviton SureSlide 6672

Lutron Ariadni AYCL-153P

Lutron Skylark Contour CTCL-153P

Lutron Diva DVCL-153P

Lutron Toggler TGCL-153P

Lutron Maestro MACL-153M

Lutron Ariadni AYLV-600P

Lutron NOVA T NTLV-600

lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Lutron Renoir II AWRMG-EAW

Lutron Nova N-600

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.