

# WISH LED

#### Project:

Fixture Type: Location:

Contact:

Wall mount • Wet location listed



## Specifications:

### **Description:**

LED wall lantern with etched white linen glass. Includes dark sky shield for full cut-off illumination or remove for a traditional lighting effect. 120V AC replaceable LED module, 623 lumens, 3000K color temperature and 90+ CRI.

#### **Construction:**

- · Black (-31) (powdercoat)
- Aluminum construction
- $\boldsymbol{\cdot}$  Etched White Linen glass cylindrical diffuser
- · LED Module is replaceable (part # 93054049)
- Flicker-free dimming to 10% brightness with most ELV type dimmers
  (See Dimming Notes)
- Title 24 compliant
- Back plate covers a standard 4" hexagonal recessed outlet box
- 4-11/16" W., 6-1/4"ht., 1"depth
- Mounting strap for outlet box included
- $\boldsymbol{\cdot}$  Six inches of wire supplied

#### Performance:

Number of Modules	1
Input Power	9W
Input Voltage	120V
Input Frequency	60Hz
Lumens/LPW	623/69.2 (LM-79) per module
ССТ	3000K
CRI	90
Life	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30° C
Max. Operating Temp	30° C
Warranty	5 year warranty
Labels	cCSAus Wet location listed
	ENERGY STAR <sup>®</sup> qualified



P6084-3130K9

#### **Dimensions:**

Width: 7" Height: 10-3/8" Depth: 8-5/8" H/CTR: 3-1/8"

Glass: 4-5/8" dia. Height: 5-7/8"

#### Catalog number:

Base	Finish	Color Temp	CRI
P6084	31 - Black	<b>30K</b> - 3000K	9 - 90 CRI



# WISH LED



### P6084-3130K9

#### **Dimming Notes:**

P6084 is designed to be compatible with many Electronic Low Voltage (ELV-Reverse Phase) controls.

The following is a partial list of known compatible dimmer controls:

#### **Electronic Low Voltage ELV Reverse Phase Controls**

Lutron	Diva Series	(Part Number DVELV-300P)
Lutron	Nova T Series	(Part Number NTELV-300)
Lutron	Vierti Series	(Part Number VTELV-600)
Lutron		(Part Number MAELV-600)
Lutron		(Part Number SPELV-600)
Leviton		(Part Number AWRMG-EAW)
Leviton		(Part Number 6615-P)

Digital type dimmers are not recommended.

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.